

ELECTRONIC COIN ACCEPTOR RM5 COMESTERO

Operating mode: serial communication. An interface card (RM927) is delivered with the coin acceptor in order to adapt the connections between this unit and the CPU board.

Coin setting:

Channel	OUT 1	OUT 2	OUT 3	OUT 4	OUT 5	OUT 6
Coin	2€	1€	50c		20c	10c

The coins accepted are: **2€, 1€, 50c, 20c y 10c.**

Game prize: Combinations of 6 dip switches (Sw1 a Sw4) are used to define the price of the game, as shown in the table.

Extra credits (bonuses): Combinations of Sw5 y Sw6 are used to program bonuses (free games).

The machine gives a bonus every time the player inserts the amount shown in the table.

CREDITS Table					BONUS Table (Sw5 / Sw6)				
Value / Credit	Sw1	Sw2	Sw3	Sw4	off/off	on/off	off/on	on/on	
By default	OFF	OFF	OFF	OFF					
10c	ON	OFF	OFF	OFF	No bonus	20c	30c	40c	
20c	OFF	ON	OFF	OFF	No bonus	40c	60c	80c	
30c	ON	ON	OFF	OFF	No bonus	60c	90c	1,2€	
40c	OFF	OFF	ON	OFF	No bonus	80c	1,2€	1,6€	
50c	ON	OFF	ON	OFF	No bonus	1€	1,5€	2€	
60c	OFF	ON	ON	OFF	No bonus	1,2€	1,8€	2,4€	
70c	ON	ON	ON	OFF	No bonus	1,4€	2,1€	2,8€	
80c	OFF	OFF	OFF	ON	No bonus	1,6€	2,4€	3,2€	
90c	ON	OFF	OFF	ON	No bonus	1,8€	2,7€	3,6€	
1€	OFF	ON	OFF	ON	No bonus	2€	3€	4€	
1,1€	ON	ON	OFF	ON	No bonus	2,2€	3,3€	4,4€	
1,2€	OFF	OFF	ON	ON	No bonus	2,4€	3,6€	4,8€	
1,3€	ON	OFF	ON	ON	No bonus	2,6€	3,9€	5,2€	
1,4€	OFF	ON	ON	ON	No bonus	2,8€	4,2€	5,6€	
1,5€	ON	ON	ON	ON	No bonus	3€	4,5€	6€	